

R11 15A

4/25/97

X-Y MATRIX TOUCHPAD

KTP-3225SN, 5VDC, 50*, 120 msec Pulse Width
KTP-3235SN, 5VDC, 10mA, 120 msec Pulse Width
KTP-32212SN, 12VDC 50*, 120 msec Pulse Width
KTP-32312SN, 12VDC, 10mA, 90 msec Pulse Width

An Output is generated with each key press.

An annunciator beeps with each keypress.

When the **PINK** wire is pulled low the **RED LED** will illuminate.

When the **WHITE** wire is pulled low the **GREEN LED** will illuminate.

***** Includes 40mA for illumination. To disable illumination, cut gray wire loop beside connector.

WIRING COLOR

RED	INPUT VOLTAGE
BLACK	GROUND
PINK	GROUND FOR RED LED
WHITE	GROUND FOR GREEN LED
GRAY	COL. 1
VIOLET	COL. 2
ORANGE	COL. 3
BROWN	ROW 1
BLUE	ROW 2
GREEN	ROW 3
YELLOW	ROW 4
TAN	CASE GROUND