Premium Touchless



The Essex Hand-E-Wave is a professional grade, touchless door activation switch, designed to help reduce the spread of viruses, bacteria, and infectious diseases.



- Advanced Doppler Radar Technology
- Ruggedized Low Profile Design
- Stainless Steel Construction
- Easy to Clean and Sanitize
- Visual and Audio Feedback
- Adjustable Detection Zone
- Timed or Toggle Output
- Narrow, Single or Double Gang
- Stainless, Black or White Finish
- Optional Manual Override
- Designed and Manufactured in the USA



HAND-E-WAVE[™]


TOUCHLESS STAINLESS STEEL SWITCH

Hand-E-Wave[™] is a ruggedized touchless switch with advanced 24GHz Doppler Radar technology. Ideal for use in public areas where sanitation is a concern including healthcare, education, commercial corporate and retail facilities, Hand-E-Wave's hands free operation helps to reduce the spread of germs including viruses, bacteria, and infectious diseases. Hand-E-Wave utilizes bidirectional microwave motion detection which provides reliable and consistent switch activation. Its' recessed design makes it easy to clean and sanitize. Hand-E-Wave can be used for new or retrofit installations including replacement of two wire mechanical switches (requires TVM).



0 • WAVE TO OPEN S Essex Electronic







1-800-KEYLESS • keyless.com

Features

Ruggedized Design Epoxy coated electronics for enhanced protection in harsh environments.

Vandal Resistant Construction 1/8" Stainless Steel faceplate. Low profile recessed design. Stainless steel, Black or White Finish

Advanced Touchless Switch Technology Hand-E-Wave utilizes 24GHz Doppler Radar Technology. A moving hand, wheelchair or cart within the detection zone activates the switch.

Visual/Audio Feedback

Visual and selectable On/Off Audio when motion is detected in the detection zone. Illuminated hand symbol changes from standby blue to relay on green.

Mounting Method

HEW-1: Narrow/Jamb. Flush mount or add spacer ring (SR-1) for surface mount. HEW-2: Single Gang. Flush mount to a single gang switchbox or add BAK BOX-SGE for surface mount. HEW-3: Double Gang. Flush mount to a double gang switchbox or add BAK BOX-DGE for surface mount.

Two Wire Retrofit Option

Two Wire Module (TWM) for replacing a two-wire mechanical switch.

ORDERING GUIDE

Part No. Description **HEW – 1B** Narrow/Jamb, Hand-E-Wave[™], Black **HEW - 1S** Narrow/Jamb, Hand-E-Wave[™], Stainless **HEW - 2B** U.S. Single Gang, Hand-E-Wave[™], Black **HEW - 2S** U.S. Single Gang, Hand-E-Wave[™], Stainless **HEW - 2W** U.S. Single Gang, Hand-E-Wave[™], White HEW - 3B U.S. Double Gang, Hand-E-Wave[™], Black **HEW - 3S** U.S. Double Gang, Hand-E-Wave[™], Stainless

- HEW 3W U.S. Double Gang, Hand-E-Wave[™], White
- Hewmo 1 Narrow/Jamb, Hand-E-Wave[™], Stainless, with Manual Override
- HEWMO 2 U.S. Single Gang, Hand-E-Wave", Stainless with Manual Override
- HEWMO 3 U.S. Double Gang, Hand-E-Wave[®], Stainless with Manual Override
 - Two Wire Module (Hardwired) for two wire switch replacement



Specifications

Power Requirements 12 to 24VAC/DC 300mw Standby, 600mw Relay On

Outputs

One SPDT Relay 2A 30VDC Resistive, 1/2A 125VAC Field selectable Timed or Toggle Output Adjustable Relay Hold Time: 1 to 30 seconds HEWMO: Adds fail safe to NC contacts and a timed 0.5 to 60 second Manual Override button.

Microwave Motion Sensor Technology

Radiated Frequency: 24.125 GHz Transmitter Radiated Power: <20 dBm EIRP Radiated Power Density: <5 mW/cm²

Detection Zone Adjustable 2 to 24 inches (typical)

Detection Mode

Motion (bidirectional)

IP Rating

HEW: IP65 HEWMO: IP64

Operating Temperature

 -40° F to + 180°F (-40° C to + 82°C)

Dimensions	Height	Width	Depth
HEW/HEWMO - 1	4½"	1 ³ /4"	1 ¹ / ₄ "
HEW/HEWMO - 2	4½"	2¾"	1 ¼"
HEW/HEWMO - 3	4½"	4½"	1 1⁄4"

Weight

HEW/HEWMO - 1	5 oz (142 gm)
HEW/HEWMO - 2	7.1 oz (200 gm)
HEW/HEWMO-3	12.8 oz (363 gm)

Certifications

FCC

Proudly Made in the USA

Hand-E-Wave™ is a trademark of Essex Electronics, Inc. © 2021 Essex Electronics, Inc. All rights reserved. LHEW.0321R3 Specifications are subject to change without prior notice.